

## G.711 Encoder/Decoder (v1.12.00) on C64x+

### FEATURES

- Compliant with the eXpressDSP™ Digital Media (XDM1.0 ISPHDEC1 and XDM1.0 ISPHENC1) interface
- A-law and U-law compression (encoding) and decompression (decoding) supported
- Operates on sets of 8 samples
- Little endian mode of operation supported
- Validated on DM644x EVM with Code Composer Studio version 3.3.38.2 and code generation tools version 6.0.15

- This codec can be used on any of TI's C64x+ based platforms such as DM644x, DM648, DM643x, DM646x, OMAP35xx and their derivatives.

### DESCRIPTION

G.711 is one of the earliest speech coders that convert 16-bit linear PCM samples to 8-bit compressed A-law or U-law samples to give a 64Kbps data rate in the encoder. Decoder expands 64Kbps bit-stream into linear PCM samples of 16-bits each at 8 KHz.

PRODUCT PREVIEW



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

eXpressDSP is a trademark of Texas Instruments.

All other trademarks are the property of their respective owners.

## Performance Summary

This section describes the performance of G711 Encoder/Decoder on DM644x EVM.

**Table 1. Configuration Table**

CONFIGURATION	ID
Encoder – 10ms	G711_001
Decoder – 10ms	G711_002
Full Duplex – 10ms	G711_003

**Table 2. Cycles Information – Profiled on DM644x EVM with Code Generation Tools Version 6.0.15**

CONFIGURATION ID	PERFORMANCE STATISTICS (MEGA CYCLES PER SECOND) <sup>(1)(2)(3)</sup>	
	AVERAGE <sup>(4)</sup>	PEAK <sup>(4)</sup>
G711_001	0.22	0.22
G711_002	0.22	0.22
G711_003	0.44	0.44

(1) Measured with frame size= 80 samples (10ms).

(2) Measured with 32K L1P configured as cache, 16K L1D configured as cache and 64KB L2 configuration configured as cache.

(3) All program and data is placed in External Memory. L1P, L1D and L2 are invalidated before each encoder and decoder execution.

(4) Average and peak MCPS measurements can vary by +/-5%.

**Note:** Cycle numbers vary across C64x+ platforms depending on the size of cache at L1P, L1D, L2, DDR2 clock and DSP clock.

**Table 3. Memory Statistics - Generated with Code Generation Tools Version 6.0.15**

CONFIGURATION ID	MEMORY STATISTICS <sup>(1)</sup>				
	PROGRAM MEMORY	DATA MEMORY			TOTAL
		INTERNAL	EXTERNAL	STACK	
G711_001	1.16	0	0.008	0.02	1.188
G711_001	0.86	0	0.508	0.02	1.388
G711_003	2.02	0	0.516	0.02	2.556

(1) All memory requirements are expressed in kilobytes (1 kilobyte = 1024 bytes).

**Table 4. Internal Data Memory Split-Up**

CONFIGURATION ID	DATA MEMORY - INTERNAL <sup>(1)</sup>		
	SHARED		INSTANCE <sup>(2)</sup>
	CONSTANTS	SCRATCH	
G711_001	Not used	Not used	Not used
G711_002	Not used	Not used	Not used
G711_003	Not used	Not used	Not used

(1) All memory requirements are expressed in kilobytes (1 kilobyte = 1024 bytes).

(2) Does not include I/O buffers.

**Table 5. External Data Memory Split-Up**

CONFIGURATION ID	DATA MEMORY - EXTERNAL <sup>(1)</sup>		
	SHARED		INSTANCE <sup>(2)</sup>
	CONSTANTS	SCRATCH	
G711_001	0	0	0.008
G711_002	0.5	0	0.008
G711_003	0.5	0	0.016

(1) All memory requirements are expressed in kilobytes (1 kilobyte = 1024 bytes).

(2) Does not include I/O buffers.

## Notes

- Total data memory for N Non-Pre-Emptive Instances = Constants + Runtime Tables + Scratch + N\*(Instance + I/O buffers + Stack)
- Total data memory for N Pre-Emptive Instances = Constants + Runtime Tables + N\*(Instance + I/O buffers + Stack + Scratch)

## References

- ITU-T Recommendation G.711:Pulse code modulation (PCM) of voice frequencies
- *G.711 Encoder/Decoder on C64x+ User's Guide* (literature number: SPRUEC9B)

## Glossary

Term	Description
Constants	Elements that go into .const memory section
Scratch	Memory space that can be reused across different instances of the algorithm
Shared	Sum of constants and scratch
Instance	Persistent-memory that contains persistent information - allocated for each instance of the algorithm

## Acronyms

Acronym	Description
EVM	Evaluation Module
ITU	International Telecommunication Union
ITU-T	Telecommunication Standardization Sector of ITU
PCM	Pulse Code Modulation
XDM	eXpressDSP Digital Media

## Revision History

This data sheet revision history highlights the changes made to the SPRS341A codec specific data sheet to make it SPRS341B.

**Table 6. Revision History of G711 Encoder/Decoder on C64x+**

SECTION	ADDITIONS/MODIFICATIONS/DELETIONS
Global	<ul style="list-style-type: none"> <li>• Modified code generation tools version to 6.0.15</li> </ul>
<a href="#">Section 1</a>	Features: <ul style="list-style-type: none"> <li>• Updated supported platforms</li> </ul>
<a href="#">Table 2</a>	Cycles Information: <ul style="list-style-type: none"> <li>• Updated Average value for Configuration ID G711_002</li> <li>• Added table footnote 'Average and peak MCPS measurements can vary by +/-5%'.</li> </ul>

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

### Products

Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>
DLP® Products	<a href="http://www.dlp.com">www.dlp.com</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>
Clocks and Timers	<a href="http://www.ti.com/clocks">www.ti.com/clocks</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>
RFID	<a href="http://www.ti-rfid.com">www.ti-rfid.com</a>
RF/IF and ZigBee® Solutions	<a href="http://www.ti.com/lprf">www.ti.com/lprf</a>

### Applications

Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Automotive	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
Broadband	<a href="http://www.ti.com/broadband">www.ti.com/broadband</a>
Digital Control	<a href="http://www.ti.com/digitalcontrol">www.ti.com/digitalcontrol</a>
Medical	<a href="http://www.ti.com/medical">www.ti.com/medical</a>
Military	<a href="http://www.ti.com/military">www.ti.com/military</a>
Optical Networking	<a href="http://www.ti.com/opticalnetwork">www.ti.com/opticalnetwork</a>
Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
Telephony	<a href="http://www.ti.com/telephony">www.ti.com/telephony</a>
Video & Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>
Wireless	<a href="http://www.ti.com/wireless">www.ti.com/wireless</a>

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2009, Texas Instruments Incorporated